

# AN7164

## 30 W BTL audio power amplifier

### ■ Overview

The AN7164 is an integrated circuit designed for 30 W ( $V_{CC} = 21\text{ V}$ ,  $8\ \Omega$ ) output power amplifier. High power output (BTL 30 W), low distortion and low noise are realized. High reliability is obtained due to various kinds of protectors built in. Furthermore, on-off of output is possible from standby terminal.



### ■ Features

- High power output
- Low distortion, Low noise
- Low shock noise when power supply is turned-on, off
- Built-in standby function
- Built-in protection circuits  
(Temperature, Overcurrent, Load short circuit, Output - GND short circuit)

### ■ Applications

- Stereo, Karaoke, TV

### ■ Block Diagram



## ■ Pin Descriptions

Pin No.	Description	Pin No.	Description
1	Ripple filter	7	Output (ch.1)
2	Negative feedback (ch.2)	8	Bootstrap (ch.1)
3	GND (Input side)	9	GND (output side)
4	Negative feedback (ch.1)	10	Output (ch.2)
5	Input	11	Bootstrap (ch.2)
6	Standby	12	Supply voltage ( $V_{CC}$ )

## ■ Absolute Maximum Ratings

Parameter	Symbol	Rating	Unit
Supply voltage *2	$V_{CC}$	30	V
Supply current	$I_{CC}$	5.0	A
Power dissipation *3	$P_D$	62.5	W
Operating ambient temperature *1	$T_{opr}$	-30 to +75	°C
Storage temperature *1	$T_{stg}$	-55 to +150	°C

Note) \*1 :  $T_a = 25^\circ\text{C}$  except power dissipation, operating ambient temperature and storage temperature.

\*2 : Without signal

\*3 :  $\theta_{j-c} = 2.0$  (°C/W)

## ■ Recommended Operating Range

Parameter	Symbol	Range	Unit
Supply voltage	$V_{CC}$	8.3 to 24	V

## ■ Electrical Characteristics at $V_{CC} = 21$ V, $R_L = 8$ $\Omega$ , $f = 1$ kHz, BTL operation, $T_a = 25^\circ\text{C}$

Parameter	Symbol	Conditions	Min	Typ	Max	Unit
Quiescent current	$I_{CQ}$	$V_{IN} = 0$ V	—	55	100	mA
Output noise voltage *1	$V_{NO}$	$R_g = 10$ k $\Omega$	—	0.85	1.3	mV
Output offset voltage	$V_{OFF SET}$	$V_{IN} = 0$ V	—	0	300	mV
Total harmonic distortion	THD	$P_O = 1$ W	—	0.07	0.3	%
Voltage gain	$G_V$	$P_O = 1$ W	49.5	51.5	53.5	dB
Maximum output power	$P_O$	THD = 10%	24	30	—	W
Ripple rejection ratio *1, 2	R.R.	$R_g = 0$ $\Omega$ , power supply ripple	45	51	—	dB
Standby current	$I_{STB}$	Pin 6 open	—	—	3	$\mu\text{A}$

Note) \*1 : Measurement through the DIN audio filter.


\*2 : Power supply ripple ..... 120 Hz Sine wave, 1V[rms]

## ■ Usage Notes


Standby-on (i.e. an application of 5 V to pin 6) under a high temperature may cause no-output due to the malfunction of rapid discharging circuit of the ripple filter. To avoid this, it is necessary to forcibly flow a current of 1 mA into pin 1 at standby-on.

## ■ Technical Information

- $P_D - T_a$  curves of HSIP012-P-0000A



## ■ Application Circuit Example



**Request for your special attention and precautions in using the technical information and semiconductors described in this book**

- (1) If any of the products or technical information described in this book is to be exported or provided to non-residents, the laws and regulations of the exporting country, especially, those with regard to security export control, must be observed.
- (2) The technical information described in this book is intended only to show the main characteristics and application circuit examples of the products, and no license is granted under any intellectual property right or other right owned by our company or any other company. Therefore, no responsibility is assumed by our company as to the infringement upon any such right owned by any other company which may arise as a result of the use of technical information described in this book.
- (3) The products described in this book are intended to be used for standard applications or general electronic equipment (such as office equipment, communications equipment, measuring instruments and household appliances).  
Consult our sales staff in advance for information on the following applications:
  - Special applications (such as for airplanes, aerospace, automobiles, traffic control equipment, combustion equipment, life support systems and safety devices) in which exceptional quality and reliability are required, or if the failure or malfunction of the products may directly jeopardize life or harm the human body.
  - Any applications other than the standard applications intended.
- (4) The products and product specifications described in this book are subject to change without notice for modification and/or improvement. At the final stage of your design, purchasing, or use of the products, therefore, ask for the most up-to-date Product Standards in advance to make sure that the latest specifications satisfy your requirements.
- (5) When designing your equipment, comply with the range of absolute maximum rating and the guaranteed operating conditions (operating power supply voltage and operating environment etc.). Especially, please be careful not to exceed the range of absolute maximum rating on the transient state, such as power-on, power-off and mode-switching. Otherwise, we will not be liable for any defect which may arise later in your equipment.
  - ☐ Even when the products are used within the guaranteed values, take into the consideration of incidence of break down and failure mode, possible to occur to semiconductor products. Measures on the systems such as redundant design, arresting the spread of fire or preventing glitch are recommended in order to prevent physical injury, fire, social damages, for example, by using the products.
- (6) Comply with the instructions for use in order to prevent breakdown and characteristics change due to external factors (ESD, EOS, thermal stress and mechanical stress) at the time of handling, mounting or at customer's process. When using products for which damp-proof packing is required, satisfy the conditions, such as shelf life and the elapsed time since first opening the packages.
- (7) This book may be not reprinted or reproduced whether wholly or partially, without the prior written permission of Matsushita Electric Industrial Co., Ltd.